

Humax F1-ACE / ID Sensor instructions – 12519V

Please follow the steps as listed and do not change anything unless specified. We have relied on satellite installers to prepare these instructions and cannot say they are without error as we do not know this receiver personally.

PLEASE BE AWARE – THESE INSTRUCTIONS WILL BE INEFFECTIVE IF YOU PERFORM A FACTORY RESET.

STEP 1 - Re-scanning the new frequency 12519V for Hope Channel:

1. Turn on your **TV** and receiver.
2. Press the **MENU** button. Use the up or down buttons to select **INSTALLATION**, press **OK**.
3. Select **SERVICE SEARCHING**, press **OK**. Enter Pin Code **0000** using number buttons.
4. Select **MANUAL SEARCH**, press **OK**.
5. Select **TRANSPONDER**, press **OK**.
6. Select **FREQUENCY**, enter **12519**.
7. **POLARITY** should be **VERTICAL** or use the right button beside **OK** to select it.
8. **SYMBOL RATE** should be **22500** or use the number buttons to type it in.
9. **FEC** should be **3/4** or use the right button to select it.
10. **NETWORK SEARCH** should have **NO** or use the right button to select it.
11. **AUTOMATIC SKIP** should be **YES**, or use the right button to select it.
12. Press **OK** to begin channel scan. A list of channels will appear including **Hope**.
13. Press **OK** and if asked if you want to save changes press **OK** again.
14. Press **EXIT** 3 times to go back to normal viewing screen.

Move Hope Channel to the channel position you want:

STEP 2 - To allocate Hope Channel a special channel number:

1. Press the **MENU** button.
2. Select **INSTALLATION**, press **OK**.
3. Select **SERVICE ORGANISING**, press **OK**. Enter Pin Code **0000** using number buttons.
4. Select **ORGANISE TV SERVICES**, press **OK**.
5. Select **ORGANISE ALL SERVICES**, press **OK**.
6. Using the up or down button find and highlight **Hope** in the new position, press the **GREEN** button.
7. Using the up button move **Hope** to the desired channel position, press **OK**.
8. Using the up or down button find and highlight the old ***Hope*** (ON FREQUENCY 12706), press the **RED** button to highlight ***Hope*** in grey. Do this with any other channels you want to delete.
9. Press **EXIT**. You will be asked if you want to save changes, press **OK**.
10. Press **EXIT** 5 times to return to normal viewing screen.

You will now watch Hope on the new channel.