

ST GOLD ST-2000F instructions – 12519V

PLEASE BE AWARE – THESE INSTRUCTIONS WILL BE INEFFECTIVE IF YOU PERFORM A FACTORY RESET.

Note 1: To 'select' an item on the on-screen menu use the 4 arrow buttons around OK to highlight that item so that it is a different colour to the rest of the items.

Note 2: *If the password 0000 does not work when you are told to enter it, you will need to contact your installer and ask them for the correct password.

STEP 1. To scan in the new frequency for Hope Channel:

1. Turn on your **TV** and receiver.
2. Press the **MENU** button on your satellite receiver remote control.
3. Use the up or down buttons to select **INSTALLATION**, press **OK**.
4. *Enter **password 0000** using the number buttons.
5. Select **SCAN TRANSPONDER**, press **OK**.
6. Select **FREQUENCY** and type in **12519** using the number buttons. Do this slowly.
7. **POLARITY** needs to be **VERTICAL**. Use the right button beside OK to select it.
8. **SYMBOL RATE** should be **22500**. If it is not use the number buttons to type it in.
9. **CODE RATE** should be **3/4**. If it is not use the right button beside OK to select it.
10. **SCAN MODE** should be **FREE CHANNEL**. If it is not use the right button beside OK to select it.
11. **NETWORK SEARCH** should be **DISABLE**. If it is not use the right button beside OK to select it.
12. Press **OK** and the receiver will search the new frequency.
13. Once the search is completed you will be asked if you want to save changes. Make sure **YES** is selected and press **OK**
14. Press the **EXIT** button 3 times until you are back at the normal viewing screen.

STEP 2. To allocate Hope Channel a special channel number:

1. Press the **MENU** button
2. Select **USER PREFERENCE**, press **OK**
3. Select **EDIT CHANNEL**, press **OK**. *Enter the **PASSWORD** as in #4 above.
4. Press the **LEFT** arrow button and "delete" should be highlighted and ticked. Select **MOVE**, press **OK**. Ensure the tick is now next to **MOVE** .
5. Press the **RIGHT** arrow button to go back to channel list on the right. Using the up or down button find and highlight **Hope**, press **OK** .
6. Using the up button move **Hope** to the desired channel position, press **OK** to lock **Hope** into that position.
7. Press the **LEFT** arrow button and highlighted **DELETE**, press **OK** to tick it.
8. Press the **RIGHT** arrow button to go back to channel list on the right. Using the up or down button select the old ***Hope***, press **OK**. A cross should appear beside it. (Make sure it is not the new Hope channel that has the cross next to it).
9. Once you have done this press the **EXIT** button and the message **DO YOU WANT TO SAVE CHANGES?** will appear. Highlight **YES**, press **OK**.
10. Now press the **EXIT** button until you are back at the normal viewing screen.

You will now watch Hope on the new channel.